
TECHNICAL DATA SHEET

DAB12-120




Specifications


	Dimensions mm - kg						Dimensions Inches - lbs						Cold Cranking Amps		
			Height	Height	Height				Height	Height	Height		20°C	0°C	-18°C
	Length	Width	Auto	Insert	Battery	Weight	Length	Width	Auto	Insert	Battery	Weight	(68°F)	(32°F)	(0°F)
DAB12-120	409	177	-	209	227	37	16.10	6.97	-	8.21	8.94	81.59	963	877	683

			Reserve Capacity - Mins					Capacity - Ampere Hour*							
	Volts	Thread size mm	75 Amps	25 Amps	20 Amps	15 Amps	8 Amps	100 Hr	48 Hr	20 Hr	10 Hr	5 Hr	3 Hr	1 Hr	
DAB12-120	12	8	63	231	295	424	886	147	138	128	117	109	95.6	77.1	

Dimensions







Applications









CYCLIC

STATIONARY


SOLAR

IVIMINITALIA

TECHNICAL DATA SHEET

DAB12-120

Charging



Nominal voltage 6 & 12 voltsDesign life $12 \text{ Years } @ 20^{\circ}\text{C}$ Operating temperature $-10 \text{ °C to } 45^{\circ}\text{C}$

Grid alloy Calcium / Tin lead alloy

Plates Flat pasted

Separator Absorbant Glass Mat
Active Material Very high purity lead
Case and cover ABS (VO on request)
Charge voltage Float 2.27 - 2.30 VPC @ 20°C

Cycling 2.40 @ 20°C

Max. 2.4 VPC Max ripple 3.5%

Charging V

Electrolyte Sulphuric acid analytical grade

purity

CHARGING CHARACTERISTICS

Floating - The optimum float voltage for a battery is temperature dependant, at 15 - 24° C the recommended value is 2.27 - 2.30V. It is recommended that battery installation sites are temperature controlled, however float voltage can be increased or decreased to compensate for temperature variations. Adjustment is calculated at +/- 3 mV per degree C.

Operating Temperature	Recommended Applied Float Voltage VPC						
0-9	2.33-2.35						
10-14	2.30-2.33						
15-19	2.27-2.30						
20-24	2.27-2.30						
25-29	2.25-2.27						
30-34	2.23-2.25						
35-40	2.21-2.23						

The most suitable charging method for battery life and performance is the constant voltage method with a limited initial current, usually limited to a maximum of $C_{20}/4$. For cyclic use we specify a short constant current phase at the end of normal charging, consult us for further details.

Charging - To obtain maximum cycle life from your battery, it is important that a suitable charging profile is used. For information about our range of chargers and our recommended charging profile, please contact us.

